

CBS ArcSafe®

Distance Is Safety®

A Group CBS Company

RSA-12A

Cutler Hammer/Square D/Westinghouse
DS - All



Installation and Operation

Distance is Safety®

WHAT STANDS
BETWEEN YOU AND
ARC-FLASH DANGER?

**WE
DO.**

2616 Sirius Road | Denton, TX 76208 | (877) 4-SAFETY | www.cbsarcsafe.com

Rev. 2/26/2016

RRS-1 – Universal Remote Racking System (Rotary)

The CBS ArcSafe® RRS-1 is a universal remote racking system capable of remotely installing and removing rotary style draw out circuit breakers without requiring any modification to the existing switchgear. Operation of the simple to use RRS-1 is quite intuitive and requires only minimal setup. When used properly, the RRS-1 allows technicians to remain outside of the arc flash boundary during the potentially dangerous racking operation.

RRS-2 – Universal Remote Racking System (Non-Rotary)

The CBS ArcSafe® RRS-2 is a universal remote racking system capable of remotely installing and removing non-rotary style draw out circuit breakers without requiring any modification to the existing switchgear. Operation of the simple to use RRS-2 is quite intuitive and requires only minimal setup. When used properly, the RRS-2 allows technicians to remain outside of the arc flash boundary during the potentially hazardous racking operation.

RRS-3 – Application Specific Remote Racking System (Rotary And Non-Rotary)

The CBS ArcSafe® RRS-3 product line is made up of various application specific remote breaker racking devices. Each standalone system allows service personnel to remotely install and remove a particular type of circuit breaker safely while stationed safely outside of the arc flash boundary during the potentially dangerous operation. The lightweight and compact design of the RRS-3 systems makes them ideal for hard to access areas where space is at a premium.

RRS-4 – PLC Based Universal Remote Racking System (Rotary)

The CBS ArcSafe® RRS-4 universal remote racking system is an updated PLC based version of the best selling RRS-1. The dual mode, source programmable, PLC based control system offers two different operating modes to choose from based on user preference or the application. The RRS-4 is capable of remotely installing and removing rotary style draw out circuit breakers without requiring any modification to the existing switchgear, allowing users to remain outside of the arc flash boundary during the potentially hazardous racking operation.

RSA – Remote Switch Actuator

The CBS ArcSafe® Remote Switch Actuator (RSA) product line is made up of various application specific remote operating devices. These products allow service personnel to remotely perform all aspects of an operation for a particular type of electrical equipment from outside the arc flash boundary – reducing or eliminating the possibility of serious injury or death resulting from an arc flash.

RSO – Remote Switch Operator

During a remote operation, the CBS ArcSafe® RSO functions as both the power supply and user interface for the device being remotely operated by the user. When paired with an applicable CBS ArcSafe® device, this portable standalone system allows service personnel to remotely perform a racking or switching procedure from outside the arc flash boundary – reducing or eliminating the possibility of injury or death resulting from an arc flash

Published and distributed by:
CBS ArcSafe®
2616 Sirius Road
Denton, Texas 76208

A division of:
GroupCBS, Inc.®
P.O. Box 1557
Gainesville, Texas 76241

Copyright CBS ArcSafe® 2013

Printed in the United States of America
Reproduction, adaptation, or translation without prior written permission is prohibited except as is allowed by law.

1 Installation

DANGER!

Before servicing any breaker, make sure that it matches the breaker discussed. If the breaker does not match the breaker described above, please call CBS ArcSafe® for more information.


ATTENTION!

The location of certain items such as mimic bus, stickers, and/or placards may interfere with the proper installation of the RSA. Please remove or reposition these items before installing the RSA.

1. Ensure that the breaker is free from any obstruction that may interfere with the proper installation of the RSA.




2. To ease installation of the RSA-12A onto the breaker, first tilt the RSA to the right as shown in the images below. This will make it easier to install the arm adapter on the motor arm, as well as the bottom handle hook on the lower handle.



3. Ensure the small aluminum locator is placed inside the hole located on the right hand side of the breaker door. The aluminum frame of the RSA should be seated flush against the cabinet before engaging the magnets. If the RSA-12A is not sitting flush with the cabinet door, check to make sure the locator is in the hole.



4. Secure the RSA-12A to the breaker by turning the handles of the two magnets 180 degrees clockwise.
5. Verify if the RSA will be switching a manually charging breaker (long arm) or an electric charging breaker (short arm). Set the RSA to operate the correct breaker by loosening the black knob and sliding it to the correct position before retightening the knob.



6. Check the Close/Trip solenoids and verify they are properly aligned with the buttons on the cabinet. The length of the Trip solenoid's plunger can be adjusted, while the Close solenoid's plunger is fixed.



The RSA-12A is ready for remote operations.



2 Operation

ATTENTION!

Please ensure that all cables are clear of moving parts. Failure to do so may result in damage to cables and/or actuator.

ATTENTION!

Please ensure that the batteries to the RSO-IIID are fully charged or that the unit is plugged into AC power.

For detailed instructions on the operation of the RSO-IIID please see the RSO-IIID Manual.

1. Ensure that the RSA is properly installed. See the Installation Section for detailed instructions.
2. Connect the cables from the RSO-IIID to the RSA.
3. The three pin twist type cable will attach to the motor control box on the RSA.
4. Turn the power switch on the RSO-IIID to the ON position.
5. Ensure that the Auto-Retract (AR) function is turned off. For detailed instructions on the AR function see the RSO-IIID manual
6. Program the settings for the RSA into the RSO-IIID. These settings can be found on the placard on the RSA. For more information on programming the RSO-IIID please refer to the RSO-IIID Technical Manual.
7. Exit the arc flash boundary
8. Once the timers have been properly set press the CHARGE/CLOSE button to actuate the motor arm and charge the breaker.
9. Press CLOSE to close the breaker.
10. Press TRIP to trip the breaker.




3 Adjustments

The RSA comes adjusted from the factory to fit most common configurations, and should not need to be adjusted in most cases. However, if adjustments do need to be performed, it is recommended that they be done on de-energized and isolated equipment to prevent possible damage or injury.

3.1 Travel Adjustment

The travel length for the motor arm may be adjusted to avoid damage to the switch.


1. Attach the RSA to the breaker as described in the Installation section of the manual. Loosen the lock-nuts on the turnbuckle of the charging arm linkage, as shown. Note that one rod end uses a left hand thread.




2. With the RSA charging arm in the UP position, rotate the turnbuckle inward to the left to move the plate upward until the upper limit switch is depressed and clicks slightly, as shown. If no click is heard, rotate the turnbuckle outward to the right to shorten the linkage until a click is heard and then repeat the first part of this step. Re-tighten the lock-nuts on the turnbuckle.



- Note that for the downward travel, this RSA is designed to work with both mechanical and electronic charging units, as indicated by the plate on the motor control box of the RSA. This requires the adjustment of one or both stops, as indicated below.



- On a manual charge breaker, loosen both the upper aluminum stop and the knob on the black delrin piece, as shown. With the RSA charging arm in the DOWN position, slowly slide the black delrin piece down until a slight click is heard and then tighten the knob. Move the upper aluminum stop down until it touches the black delrin piece and then tighten the stop.




- On an electric charge breaker, loosen both the lower aluminum stop and the knob on the black delrin piece, as shown. With the RSA charging arm in the DOWN position, slowly slide the black delrin piece down until a slight click is heard and then tighten the knob. Move the lower aluminum stop up until it touches the black delrin piece and then tighten the stop.



3.2 Solenoid Position Adjustment

The position of the solenoid on this RSA can be adjusted to ensure that the plungers are aligned with the close and trip buttons.

6. Loosen the bolts on the solenoid mount and move the assembly up or down to align the plungers over the close and trip buttons, as shown.



7. Re-tighten the two bolts on the solenoid mount.


3.3 Plunger Depth Adjustment

The operation depth of the solenoid on this RSA can be adjusted to accommodate differences in the button-press depth requirements.

8. To increase the solenoid plunger depth, loosen the nut on the solenoid plunger, and turn the black end counter-clockwise. Test the depth by operating the appropriate plunger with the RSO, and re-tighten the nut.



9. To decrease the solenoid plunger depth, loosen the nut on the solenoid plunger, and turn the black end clockwise. Test the depth by operating the appropriate plunger with the RSO, and re-tighten the nut.





Distance Is Safety®

A Group CBS Company

RSA-12A
Installation and Operation

2616 Sirius Road
Denton, TX 76208
Tel: 877-4-SAFETY
Fax: 940-382-9435
Website: www.CBSArcSafe.com
Email: info@CBSArcSafe.com

DANGER!

Ensure that personnel using this equipment are adequately trained in the operation of the switchgear they are planning to work with; that they are correctly stationed outside the arc flash boundary; and that they comply with all applicable Federal, State, Local, and In-house safety regulations and procedures. Attention should be given to distance, angle, and personal protective equipment (PPE).