



### DESCRIPTION

The **CBS ArcSafe® RSA-134H** remote switch actuator (RSA) is designed to operate the Square D Type QMB Safelex 2000 A panelboard switch (PBS) with no modification to existing electrical equipment thanks to CBS ArcSafe's magnetic latching system. The lightweight, portable RSA-134H allows technicians to remotely close or trip the Square D PBS from a safe distance of up to 300 feet while remaining stationed outside the arc-flash boundary. The RSA-134H is compatible with Square D QMB Safelex panelboard switches rated at 2000 A. Typical applications include switching and protection of low-voltage AC and DC power distribution systems. Designed, manufactured, and assembled in the United States, all RSA units are portable with fast and easy setup. They offer mechanical and/or electrical safety protection, are adjustable to fit unique electrical equipment configurations, reduce requirements for personal protection equipment, and help customers with NFPA 70E arc-flash safety compliance. Optional features include a radio remote with range up to 300 feet, a 24 V DC LED light, a wireless video camera system with an LCD monitor, and a rugged protective case assembly.

### SPECIFICATIONS

WEIGHT:	24 lbs
DIMENSIONS:	16.6" H x 9.1" W x 9.8" D
POWER CONSUMPTION:	100 W
OPERATING DISTANCE:	25–300 feet
COMPATIBILITY:	Square D Type QMB Safelex
CONTROL/POWER SOURCE:	CBS ArcSafe® RSO-I AR control console

### OVERVIEW

- Remote operation from up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup; no equipment modification required
- Reduces or eliminates need for arc-flash hazard suits
- Designed, manufactured, and assembled in the USA

