



DESCRIPTION

The **CBS ArcSafe RSA-145E** remote switch actuator is designed to remotely close or trip all size ABB/Sace Isomax S7 low-voltage molded case circuit breakers from a safe distance stationed outside the arc-flash perimeter. Capable of operation from up to 300 feet away, this custom-built actuator reduces or eliminates the need for arc-flash hazard suits. The actuator's light weight and portability allow for quick installation in even the hardest-to-access areas.

SPECIFICATIONS

| | |
|-----------------------|--|
| WEIGHT: | 8.4 lbs |
| DIMENSIONS: | 8.3"L x 7.9"W x 4.7"D |
| POWER CONSUMPTION: | 50W |
| OPERATING DISTANCE: | 25-300 feet |
| COMPATIBILITY: | ABB/SACE Isomax S7 (1200A) Molded Case Circuit Breaker |
| CONTROL/POWER SOURCE: | CBS ArcSafe® RSO-I AR control console |



OVERVIEW

- Remote operation from up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup, no equipment modification required
- Quick installation and removal from gear
- Adjustable travel and locators to accommodate entire product line
- Reduces or eliminates need for arc-flash hazard suits
- Eliminates all hazardous manual contact with gear during operation
- Designed, manufactured, and assembled in the USA

