



### DESCRIPTION

The **CBS ArcSafe® RSA-162** remote switch actuator (RSA) is designed to operate the General Electric EntelliGuard G circuit breaker without having to make any modifications to existing electrical equipment thanks to CBS ArcSafe's magnetic latching system. The lightweight, portable RSA-162 allows technicians to remotely charge, close, or trip the circuit breaker from a safe distance of up to 300 feet while remaining stationed outside the arc-flash boundary. The RSA-162 is compatible with GG/GJ/GH/GK-04/07/08/10/13/16/20/25/32/40/50/64 circuit breakers with ratings from 400-6,000 A. Typical applications include providing advanced circuit protection, limiting arc-fault energy, and preserving system coordination for power distribution systems. Designed, manufactured, and assembled in the USA, all RSA units are portable, fast, and easy to set up, offer mechanical and/or electrical safety protection, are adjustable to fit unique electrical equipment configurations, reduce the requirements for personal protection equipment (PPE), and help customers with NFPA 70E arc-flash safety compliance. Optional features include radio remote with range up to 300 feet, 24 V DC LED light, wireless video camera system with LCD monitor, and rugged protective case assembly.

### SPECIFICATIONS

WEIGHT:	25.5 lbs
DIMENSIONS:	18.53"H x 19.20"W x 6.27"D
POWER CONSUMPTION:	50W
OPERATING DISTANCE:	25-300 feet
COMPATIBILITY:	GG/GJ/GH/GK-04/07/08/10/13/16/20/25/32/40/50/64 circuit breakers with ratings from 400-6000A
CONTROL/POWER SOURCE:	CBS ArcSafe® RSO-IIID control console

### OVERVIEW

- Remote operation from up to 300 feet
- Lightweight, portable, and adjustable
- Simple setup; no equipment modification required
- Reduces or eliminates need for arc-flash hazard suits
- Designed, manufactured, and assembled in the USA

