



DESCRIPTION

The **CBS ArcSafe® RSA-184** remote switch actuator (RSA) is designed to operate the Cutler-Hammer FDPW fusible panelboard switch without having to make any modifications to existing electrical equipment thanks to CBS ArcSafe's magnetic latching system. The lightweight, portable RSA-184 allows technicians to remotely close or trip the circuit breaker from a safe distance of up to 300 feet while remaining stationed outside the arc-flash boundary. The RSA-184 is compatible with 30, 60, and 100 A twin, horizontal fused switches with a height of 5.375". Typical applications include commercial, industrial, and service entrance applications to protect and switch feeder and branch circuits. Designed, manufactured, and assembled in the USA, all RSA units are portable, fast, and easy to set up, offer mechanical and/or electrical safety protection, are adjustable to fit unique electrical equipment configurations, reduce the requirements for personal protection equipment (PPE), and help customers with NFPA 70E arc-flash safety compliance. Optional features include radio remote with range up to 300 feet, 24 V DC LED light, wireless video camera system with LCD monitor, and rugged protective case assembly.



SPECIFICATIONS

WEIGHT:	9 lbs
DIMENSIONS:	8.3"W x 4.5"H x 6.2"D
POWER CONSUMPTION:	30W
OPERATING DISTANCE:	25-300 feet
COMPATIBILITY:	30, 60, & 100 A twin, horizontal fused switch, 5.375" height
CONTROL/POWER SOURCE:	CBS ArcSafe® RSO-I control console

OVERVIEW

- Remote operation from up to 300 feet
- Lightweight, portable, and adjustable
- Simple setup; no equipment modification required
- Reduces or eliminates need for arc-flash hazard suits
- Designed, manufactured, and assembled in the USA

