



**POWERED BY**  
**M18 REDLITHIUM**



## DESCRIPTION

The **CBS ArcSafe® RSA-286G** allows technicians to remotely operate Siemens 3VA6 circuit breakers from a safe distance while remaining stationed outside of the arc flash boundary. Installation and operation does not require any modifications to the existing electrical equipment.

The **CBS ArcSafe® RSA-286G** is compatible with all configurations of Siemens 3VA6 circuit breakers. The **CBS ArcSafe® RSA-286G** is a cost-effective solution for keeping operators safe when compared to other arc flash mitigation alternatives.

## SPECIFICATIONS

<b>WEIGHT:</b>	15 lbs.
<b>DIMENSIONS:</b>	28.0" x 6.4" x 5.5" (W,H,D)
<b>POWER CONSUMPTION:</b>	50 W
<b>OPERATING DISTANCE:</b>	25-300'
<b>COMPATIBILITY:</b>	Siemens 3VA 1000 A
<b>CONTROL/POWER SOURCE:</b>	CBS ArcSafe® RSO-IAR-M18 Control Console

## OVERVIEW

- Remote operation up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup, no equipment modification required
- Quick installation and removal from gear
- Adjustable travel and locators to accommodate entire product line
- Reduces or eliminates need for arc flash hazard suits
- Eliminates all hazardous manual contact with gear during operation
- Designed, manufactured, and assembled in the USA
- Powered by Milwaukee M18 RedLithium Battery Pack

