



DESCRIPTION

The **CBS ArcSafe® RSA-97B** remote switch actuator (RSA) is designed to operate the Square D Model 4 motor control center (MCC) with no modification to existing electrical equipment, thanks to CBS ArcSafe's magnetic latching system. The lightweight, portable RSA-97B allows technicians to remotely close or trip the Square D MCC from a safe distance of up to 300 feet while stationed outside the arc-flash boundary. The RSA-97B is compatible with the Square D Model 4 MCC, size 5 and main, recessed mounted MCCs, as well as flange-mounted disconnects. Typical applications include protection and control of low-voltage MCCs. Designed, manufactured, and assembled in the United States, all RSA units are portable, with fast and easy setup. They offer mechanical and/or electrical safety protection, adjust to fit unique electrical equipment configurations, reduce requirements for personal protection equipment, and help customers meet NFPA 70E arc-flash safety compliance. Optional features include a radio remote with a range of up to 300 feet, a 24 V DC LED light, a wireless video camera system with an LCD monitor, and a rugged protective case assembly.

SPECIFICATIONS

WEIGHT:	18.5 lbs.
DIMENSIONS:	8" H x 11" W x 7.75" D
POWER CONSUMPTION:	50 W
OPERATING DISTANCE:	25–300 ft.
COMPATIBILITY:	Square D Model 4, size 5 and main recessed mounted and flange-mounted disconnects
CONTROL/POWER SOURCE:	CBS ArcSafe® RSO-I AR control console

OVERVIEW

- Remote operation from up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup; no equipment modification required
- Reduces or eliminates need for arc-flash hazard suits
- Designed, manufactured, and assembled in the USA

