



DESCRIPTION

The **CBS ArcSafe® RSA-152G** remote switch actuator (RSA) is designed to operate the Boltswitch T Series of bolted pressure switches (BPS) with no modification to existing electrical equipment, thanks to CBS ArcSafe's magnetic latching system. The lightweight, portable RSA-152G allows technicians to remotely close or trip the Boltswitch BPS from a safe distance of up to 300 feet while stationed outside the arc-flash boundary. The RSA-152G is compatible with the 400-1200 A Boltswitch T Series, including T265-268, T325-328, and T365-368. Typical applications include low-voltage power control and distribution. Designed, manufactured, and assembled in the United States, all RSA units are portable, with fast and easy setup. They offer mechanical and/or electrical safety protection, adjust to fit unique electrical equipment configurations, reduce requirements for personal protection equipment, and help customers with NFPA 70E arc-flash safety compliance. Optional features include a radio remote with range up to 300 feet, a 24 V DC LED light, a wireless video camera system with an LCD monitor, and a rugged protective case assembly.

SPECIFICATIONS

WEIGHT:	17.5 lbs
DIMENSIONS:	7" H x 10.25" W x 9" D
POWER CONSUMPTION:	50 W
OPERATING DISTANCE:	25–300 feet
COMPATIBILITY:	Boltswitch T Series, 400-1200 A
CONTROL/POWER SOURCE:	CBS ArcSafe® RSO-I AR control console

OVERVIEW

- Remote operation from up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup; no equipment modification required
- Reduces or eliminates need for arc-flash hazard suits
- Designed, manufactured, and assembled in the USA

